



FEATURES



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



AVR

AVR is a device often solid state, for controlling the output



CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



VOLTMETER

It is a gauge for out put voltage of generator set.



CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.



DUAL ELEMENT AIR FILTER

GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	0 ,9
Maximum Power (kW)	1
AC Nominal Current (A)	3 ,4
DC Rated Corrent (A)	8,3
Voltage (V)	
Frequency (Hz)	
Phase Number	
Power Factor	
Fuel Consumption %100 (lt/h)	1,05
Fuel Consumption %75 (lt/h)	0,73
Fuel Consumption %50 (lt/h)	0,52
Noise Level (dB(A))	75
Sound Level (LwA)	9 5
Pole Number	2
Output Receptacle	1x16A/250v

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)





ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	2,8
Engine Output (kW)	2,1
Bore and Stroke	56x40
Compression Ratio	8,9
Cylinder Number	1
Displacement (ml)	98
Fuel Type	Gasoline
Oil Capacity (L.)	0,35
Fuel Tank Capacity (L.)	7
Starting System	Manual
Cooling System	Air Cooled

DIMENSIONS AND WEIGHT

Width (mm.)	395
Lenght (mm.)	485
Height (mm.)	430
Dry Weight (kg.)	27