



FEATURES

FUEL GAUGE

Fuel gauge is on the fuel tank

OHV

Over Head Valve easy to maintenance

OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.

AVR

AVR is a device often solid state, for controlling the output

CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.

LED DISPLAY

LED screen to monitor voltage and current with hourmeter

CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.

DUAL ELEMENT AIR FILTER

LARGE CAPACITY FUEL TANK

15-25lt

-Z μ v Ÿ u u Ç À Æ Ç % v] v P } v (μ o š v l %] š Ç •

GENERAL SPECIFICATIONS

3 Phase, 50 Hz, PF 0.8

AC Rated Power	kVA(kW)	1 0 (8)
Maximum Power	kVA(kW)	1 1 (8,8)
AC Nominal Current (A)		1 4 ,4
Voltage (V)		230/400
Frequency (Hz)		
Phase Number		
Power Factor		
Fuel Consumption %100 (lt/h)		7,3
Fuel Consumption %75 (lt/h)		5,9
Fuel Consumption %50 (lt/h)		4,33
Noise Level (dB(A))		82,6

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)



ENGINE SPECIFICATIONS

Speed (Rpm)	36 00
Power (Hp)	18
Fuel Type	Gasoline
Oil Capacity (L.)	1,7
Fuel Tank Capacity (L.)	16
Starting System	Electric/Manual

DIMENSIONS AND WEIGHT

Width (mm.)	740
Lenght (mm.)	910
Height (mm.)	750
Dry Weight (kg.)	117